

LED Circular Three Spoke 10w

Exterior



Built-in Sensor automatically dims to 1W when not activated

LED Circular Three Spoke
EFX-LACC10W

LED Circular Three Spoke - EFX-LACC10W


The Eco-FX LED Circular Three Spoke offers high luminosity COB LEDs giving efficient heat dissipation and produces a softer light. The long life driver offers constant current and voltage. Emergency Control Gear available.

Dimming

- It will automatically turn down the brightness when nobody is there. And the light will quick start to enter in a full brightness status when somebody is there.
- It can avoid the lifetime reduction of the lamp caused by the frequent start
- Automatically dims to 1w when not activated

Sensor(s)

- Time setting: 8sec – 12min (adjustable)
- Detection range: 1m – 8m (radii), adjustable
- Standby power: <0.9W
- Detection angle: 360°



- white
- silver
- black

	Technical 10w
Product Code	EFX-LACC10W
Size	Ø280mm x 78mm
Sensor Beam Angle	360°
Input Voltage	220-240Vac
Frequency	50/60 Hz
Power Factor	0.93
Chip Set	Bridgelux
Efficiency (LOR)	35%
Colour Temperature	Warm White 3000k/4000k/5000k
Lumen	Warm White 800lm
Efficacy	80lm/w
CRI	Warm White >80
LED Life	50,000Hrs
Operating Temperature	-40° / +50°
IP Rating	IP65
Emergency	3hr
Emergency Wattage	2W
Emergency Lumen	120lm

