

# LED Emergency Exit Sign 7w

Maintained










LED Emergency Exit Sign - EFX-HSES

## LED Emergency Exit Sign - EFX-HSES

The Eco-FX LED Emergency offers high luminosity COB LEDs giving efficient heat dissipation and produces a softer light. The long life driver offers constant current and voltage. Over charge and Discharge protection.

Technical 7w	
Product Code	EFX-HSES
Size	390mm x 190mm x 60mm
Convert Voltage	150-180Vac
Frequency	50/60 Hz
Discharge Current	180W 250MA
Charging Current	60-120MA
Power Factor	0.93
Chip Set	SMD 3528
Efficiency (LOR)	95%
Colour Temperature	Warm White 3000k
Lumen	Warm White 110lm
Efficacy	36.66
CRI	Warm White >80
LED Life	50,000Hrs
Operating Temperature	-40° / +50°
IP Rating	20
Discharge Durations	3Hrs
Battery	4.8V, 1500MAH, NI-CAD

### Eco-FX Limited

Office 1, 192 Shoreham Street  
Sheffield S1 4SQ, UK

t: +44 (0) 114 321 9610  
e: enquiries@eco-fx.co.uk

w: [www.eco-fx.co.uk](http://www.eco-fx.co.uk)

Issue March 2013

©Copyright 2013 - Eco-FX Limited